

Article Number: 383382

1P/12V Coil (SAE J560, SAE J1128, SAE J3082)



Description	adhesive lined heat shrink sealed
Categories	Coil
Standards	SAE J560 , SAE J1128 , SAE J3082
Industries	Commercial vehicles

Electrical Details and Temperature Resistance

Temperature resistance [in °C]	-65.0 - 65.0
Voltage [in V]	12

Packaging and Order Details

Packaging	bulk packaging
-----------	----------------

Design Features

Branding	ERICH JAEGER
----------	--------------

Material

Cable color	black
Contact surface	brass alloy
Housing color	silver-colored
Housing material	zinc
Material of cable	TPE

Connectivity

No. of connected plugs	2
No. of connected sockets	0
No. of poles	01
Outlet open or closed	n.a.

Norms and Standards

Protection	IP 54
------------	-------

Measures and Dimensions

Outer coil diameter [in mm]	80,00
Wire cross-sectional area	4 AWG
Working length [in feet]	15,00